

VISTA 48



Control Panel

The new Vista 48 intruder panel offers an extensive feature set at a remarkable competitive price. This hybrid panel offers 64 zones in total of which 56 zones can be wireless. Arming/disarming can be performed wireless by keyfobs. For controlling external equipment the Vista 48 is equipped with 2 outputs. These can be extended with max. 16 programmable rely-outputs or a X10 transmitter that can

drive up to 16 X10 modules. This panel even gives you the possibility to define your own zone functions. Last but not least we should mention that you will find 4 programmable keys on the keypads. Each can be individually programmed with a macro to e.g. switch on a lamp, open the garage door or arm the system while bypassing specific zones.

Features:

- Complies to EN 50131-1 and TS 50131-3 Grade 2, Class II
- Complete intruder panel
- Expandable with wired or wireless zones
- Can be divided in 3 sub-systems
- Keypads with 4 programmable keys
- Up- & Downloading/Remote service through Compass software
- 48 User codes with individual authorisation levels
- 32 Schemes for limiting access, relay-outputs or automatic arming/disarming
- Integrated analogue dialler
- X10 compatible
- Activity monitoring

VISTA 48

Control Panel

Specifications:

Specification	
Zones:	
- Wired only (built-in)	8
- Wireless only	16
- Wired or wireless	40
Doubling zones	8
Zone functions	23
Self-defined zone functions	4
No. of keyfob	4
No. of keypads	8+2 6270
No. of partitions	3
Outputs (relay or X10)	2/18
Output functions	24
Automatic arm/disarm times	24
Event memory	254

Software:

Designed for installers, this Compass software allows you to up- or download the programming of the Vista 48 panel from a remote location (through telephone lines) or locally. It is also possible to service the panel with this software. Compass contains a database to store each of your programmed VISTA panels. The CIA-EU modem is fully compatible with the Compass software.

Product versions:

Version	Languages
Vista 48B	English, German and Dutch
Vista 48C	English, Hebrew, Canadian-French and Russian
Vista 48D	English, Spanish, Italian and Portuguese
Vista 12E	English (South African Market)

Honeywell Security

(EMEA head quarter)
1198, Avenue du Docteur Maurice Donat
BP1219, 06254 Mougins Cedex
France
Tel : +33 (0) 492 942 950
Fax : +33 (0) 492 942 960
www.honeywell.com/security/emea

Peripherals:

The Vista 48B is supported by a wide range of ECP-bus peripherals:

6148 ICON

- LCD display with icons
- Icons on keypad

6164 ICON

- 2 x 16 Alphanumeric LCD display
- Icons on keypad;
- 4 zones and one relay output on board

6160RFH

- 2 x 16 Alphanumeric LCD display
- Icons on keypad;
- 868 MHz. RF-receiver on-board

6270

- B&W graphic touch screen keypad
- Menu-driven prompts
- Built-in message centre

4219

- 8 zone expansion module
- Complete with housing

4229

- 8 zone + 2 relay expansion module
- Complete with housing

4204

- 4 relay expansion module
- Complete with housing

5882H

- 868 MHz. RF-receiver for 58xxH transmitters
- Complete with housing

5882EUHS

- 868 MHz. RF-receiver for Domonial transmitters
- Complete with housing

Domonial wireless (868 MHz.):

TCM800HF

- Panic button (1 button)
- Including transmission LED

TCB800M or TC805HF

- 4 button keyfob
- 5 Functions

DTO800HF

- Smoke detector
- Combined optical/fixed temperature/rate-of-rise

DOT800GY-B

- Magnetic contact
- Extra zone input

BVA800HF-B

- Glassbreak detector
- Acoustical, omnidirectional

IR800M

- PIR sensor (11 x 12m)

IRPI800M

- PIR sensor (11 x 12m)
- Pet immune

SHK1-800GY-B

- Shock sensor

CLI810HF-B

- Keypad

CSK800HF-B

- Keypad
- Including TAG reader

Honeywell House
Treur Close, Waterfall Park
Midrand 1685, PO Box 6674
Halfway House, 1685
South Africa
Tel: +27 (0)11 695 8000
Fax: +27 (0)11 805 1510
www.honeywell.com/security/za

Netwerk 121, 1446 WV Purmerend
The Netherlands
Tel +31 (0) 299-410200
Fax +31 (0) 299-410201
www.honeywell.com/security/nl